

## Description:

TRI ADAPTER 18" WITH  
PASS THRU & PUSH TO  
RESET BREAKERS

INCOMING: 1 EACH 30  
AMP, 120/208V (NEMA L21-  
30) PLUG ON 18" OF 10/5  
SO CABLE.

OUTPUTS: 3 EACH 20  
AMP, 125V (NEMA 5-20)  
DUPLEX RECEPTACLES.  
1BLK, 1RED, 1BLU.

1 EACH 30 AMP, 120/208V  
(NEMA L21-30)  
CONNECTOR ON 18" OF  
10/5 SO CABLE.

BREAKERS: 3 EACH  
20AMP PUSH TO RESET  
CIRCUIT BREAKERS W/  
PHASE INDICATORS.

## Specifications:

<b>Rating:</b>	30 Amp, 3 Phase, 4P, 5W, 120/208V
<b>Incoming:</b>	1 EACH 30 AMP, 120/208V (NEMA L21-30) PLUG
<b>Cord Type:</b>	10/5 SO
<b>Outputs:</b>	3 EACH 20 AMP, 125V (NEMA 5-20) DUPLEX RECEPTACLES. 1BLK, 1RED, 1BLU.  1 EACH 30 AMP, 120/208V (NEMA L21-30) CONNECTOR ON 18" OF 10/5 SO CABLE.
<b>Enclosure:</b>	Custom PVC
<b>Enclosure Dimensions:</b>	6.5"L x 4.5"W x 3"H
<b>Cord Length:</b>	18" on both ends
<b>Weight:</b>	5 lbs.

